

DMX Control 512™

The DMX Control 512 offers control of up to 16 fixtures with a maximum of 32 channels each.



The DMX Control 512 supports ROBE and all other popular lighting brands. A show of up to 1024 Scenes can be created consisting of Presets and Chases. The DMX Control 512 uses Flash memory for easy software updates via a computer (RS 232). The DMX Control 512 is suitable for all range of AT, CT and LT series.

Spécifications Techniques

Contrôle et programmation

- Real time control of Moving Heads and Scanners
- Total 512 DMX Channels
- Control 16 Projectors up to 32 channels each
- 1024 Programmable Scenes
- 512 Programmable Presets
- 256 Chases + 48 pre-recorded
- 256 Shows
- Effects Engine
- Large Fixture Library
- Factory ready Color, Gobo, Focus, and Effects Presets
- MIDI Function
- 1 Large rotary wheel for Menu and Control
- 8 Faders x 4 Banks
- 1 (3pin) DMX Output
- 1 Polarity switch
- MIDI-In port, MIDI-Out port
- RS-232 Port for PC interface
- RCA Audio Input for Chases

Spécification électrique

- Power supply: 120/230V via external Power Supply 9V DC/500mA

Spécification mécanique

- Height: 120 mm (47.2")
- Width: 133 mm (52.4")
- Length: 483 mm (19.0")
- Weight: 3.2 kg (7.1 lbs)

Accroche

- Rack size: 19" 3U rack mountable, 3 spaces